

Redundant 200W Media Converter Chassis Power Supply Module for ETCHS2U

Product ID: ETCHS2UPSU



The ETCHS2UPSU Redundant / Replacement 200W Chassis Power Module for ETCHS2U lets you add a redundant power supply, or keep a replacement power supply on hand for your ETCHS2U media converter chassis.

A hot-swappable, modular design allows a second media converter redundant power supply to be removed or installed while the chassis is still operating, avoiding unnecessary downtime. The power supply is installed using thumbscrews for a quick and easy installation that doesn't require additional tools.

Backed by a StarTech.com 2-year warranty and free lifetime technical support.

Certifications, Reports and Compatibility

Applications

- Install into the ETCHS2U media converter chassis to provide redundancy
- Store a replacement power supply to have it on hand in the event of a failure

Features

- Hot-swappable, simple installation
- Redundant / replacement power supply for ETCHS2U
- 200W Output
- Active Power Factor Correction (PFC)

Performance

Warranty	2 Years
MTBF	65,000 Hours (25C)
Output Power	200W
Power Factor Correction	Active
Efficiency Rating	90% (Typical Load)

Power

Power Source	Standard 120V Power Cords
Input Voltage	110V-240V AC
Input Current	2.2A @ 115VAC / 1.2A @ 230VAC
Output Voltage	12V DC
Output Current	16.6A
Power Consumption (In Watts)	60

Environmental

Operating Temperature	0C to 60C (32F to 140F)
Storage Temperature	-10C to 70C (14F to 158F)
Humidity	5~90% RH Non-condensing

Physical Characteristics

Material	Steel
Product Length	8.3 in [21.2 cm]
Product Width	8.9 in [22.5 cm]
Product Height	4.7 in [12 cm]
Weight of Product	35.3 oz [1000 g]

Packaging Information

Package Length	14.0 in [35.6 cm]
----------------	-------------------



Package Width	8.4 in [21.4 cm]
Package Height	2.7 in [69 mm]
Shipping (Package) Weight	3.9 lb [1.8 kg]

What's in the Box

Included in Package	Replacement 200W Power Module for ETCHS2U
---------------------	---

****Product appearance and specifications are subject to change without notice.***

