

## 2x1 HDMI + VGA to HDMI Converter Switch w/ Automatic and Priority Switching – 1080p - TAA

**Product ID:** VS221VGA2HD



The VS221VGA2HD HDMI & VGA Auto Switch lets you connect an HDMI and a VGA audio/video source to the same HDMI display or projector, and automatically or manually switch between which video source is displayed. The multi-input A/V switch supports video resolution up to 1920x1200 (1080p) and includes mounting hardware for a tidy professional installation.

The A/V switch features built-in VGA conversion, enabling you to connect an HDMI and a VGA video source to the same HDMI display without the use of additional adapters or scalars.

The VS221VGA2HD ensures hassle-free operation with two different auto switching modes: automatic switching that detects and selects a newly connected device, as well as priority selection which lets you choose which port should be activated by default for automatic switching.

This A/V switch has been designed with the boardroom and classroom in mind: the VS221VGA2HD features VGA and HDMI inputs to support a wide range of devices, and the built-in converter makes it easy to connect to the room's display without the use of additional adapters. Plus, automatic switching encourages on-the-fly collaboration among students or co-workers, by making it easy to share your projector between multiple source devices.

If you are looking for a similar device with VGA output, please see our VS221HD2VGA.

The VS221VGA2HD is TAA compliant and backed by a StarTech.com 2-year warranty, and free lifetime technical support.

### Certifications, Reports and Compatibility



## Applications

- Automatically switch between your set top box or computer in a home theatre environment
- Share a classroom or conference room projector with VGA and HDMI video sources
- Connect and switch between VGA and HDMI video sources on a test bench, for troubleshooting computers
- Switch between VGA and HDMI video sources on your digital signage display in hospitals, shopping centers, or schools

## Features

- Accommodates both VGA and HDMI input devices in a single switch with HDMI output, saving hassle and expense by reducing the need for adapters
- Effortless control with automatic and priority port selection
- Ideal for classroom and boardroom display applications, allowing presenters to connect a wide range of devices
- Supports video resolutions up to 1920x1200 / 1080p
- Mounting hardware included

---

### Hardware

Warranty	2 Years
AV Input	HDMI VGA
Ports	2
AV Output	HDMI
Audio	Yes

---

### Performance

Maximum Analog Resolutions	1920x1200
Maximum Digital Resolutions	1920x1200
Supported Resolutions	Supports resolutions up to 1920x1200 / 1080p
Wide Screen Supported	Yes
Audio Specifications	2-channel 3.5mm stereo audio (VGA)

7.1 surround sound (HDMI)

---

**Connector(s)**

Connector A	1 - HDMI (19 pin) 1 - VGA (15 pin, High Density D-Sub) 1 - 3.5 mm Mini-Jack (3 Position)
Connector B	1 - HDMI (19 pin)

---

**Indicators**

LED Indicators	1 - VGA Port Selected 1 - HDMI Port Selected
----------------	---

---

**Power**

Power Source	AC Adapter Included
Input Voltage	100 - 240 AC
Input Current	0.3 A
Output Voltage	5 DC
Output Current	1 A
Center Tip Polarity	Positive
Power Consumption (In Watts)	5

---

**Environmental**

Operating Temperature	0C to 40C (32F to 104F)
Storage Temperature	-20C to 60C (-4F to 140F)
Humidity	0%~80%

---

**Physical Characteristics**

Color	Black
Material	Steel
Product Length	4.0 in [10.2 cm]

Product Width	2.1 in [5.4 cm]
Product Height	1.1 in [2.9 cm]
Weight of Product	8.0 oz [226 g]

---

**Packaging Information**

Package Quantity	1
Package Length	9.4 in [23.9 cm]
Package Width	6.2 in [15.7 cm]
Package Height	2.6 in [6.6 cm]
Shipping (Package) Weight	1.5 lb [0.7 kg]

---

**What's in the Box**

Included in Package	1 - VGA+HDMI to HDMI converter switch
	1 - mounting kit
	1 - universal power adapter (NA, EU, UK, ANZ)
	1 - instruction manual

---

*\*Product appearance and specifications are subject to change without notice.*